

Exact solution of the time-dependent harmonic plus an inverse harmonic potential with a time-dependent electromagnetic field

Cem Yüce*

Physics Department, Middle East Technical University, 06531 Ankara, Turkey

(February 1, 2008)

Abstract

In this article, the problem of the charged harmonic plus an inverse harmonic oscillator with time-dependent mass and frequency in a time-dependent electromagnetic field is investigated. It is reduced to the problem of the inverse harmonic oscillator with time-independent parameters and the exact wave function is obtained.

PACS numbers: 03.65.Ge

Typeset using REVTeX

*e-mail: yuce@metu.edu.tr

I. INTRODUCTION

A time-dependent quantum system with a Hamiltonian which contains a singular term

$$\hat{H} = \frac{\hat{\mathbf{p}}^2}{2m(t)} + \frac{m(t)}{2}\omega^2(t) \hat{\mathbf{q}}^2 + \frac{C}{m(t)\hat{\mathbf{q}}^2}, \quad (1)$$

is one of the rare examples admitting exact solution and has been subject of great interest in a variety of contexts [1–10], because of its various applications in different areas of physics. For example, it is used for constructing exactly solvable models of interacting many-body systems [1,2], for modelling polyatomic-molecules [3] and for coherent-state formalism [11]. The Hamiltonian in Eq. (1) has been studied and the exact solution was obtained by using the Lewis and Riesenfeld invariant method and by making canonical and unitary transformations [5–9]. Although the exact solution of the time-dependent charged harmonic oscillator in a time-varying electromagnetic field is known [12], the charged harmonic plus inverse harmonic oscillator problem in a time-varying electromagnetic field has not yet been solved exactly.

In this letter we take the following Hamiltonian into account

$$\hat{H} = \frac{[\hat{\mathbf{p}} - q\hat{\mathbf{A}}(t)]^2}{2m(t)} + \frac{m(t)}{2}\omega^2(t) \hat{\mathbf{q}}^2 + \frac{C}{m(t)\hat{\mathbf{q}}^2} + q\hat{\phi}(t) = i\frac{\partial}{\partial t}, \quad (2)$$

where we have set $\hbar = 1 = c$. By making some transformations, Eq. (2) is reduced to

$$\frac{\hat{\mathbf{p}}'^2}{2} + \frac{C}{\hat{\mathbf{q}}'^2} = if(t')\frac{\partial}{\partial t'}, \quad (3)$$

where $f(t)$ is a time-dependent function. Finally, Eq. (3) is integrated.

II. METHOD

The Hamiltonian for the charged harmonic plus inverse harmonic oscillator constrained to move in the $x - y$ plane is given

$$\hat{H} = \frac{[\hat{\mathbf{p}} - q\hat{\mathbf{A}}(t)]^2}{2m(t)} + \frac{m(t)}{2}\omega^2(t) (\hat{x}^2 + \hat{y}^2) + \frac{C}{m(t)(\hat{x}^2 + \hat{y}^2)} + q\hat{\phi}(t) = i\frac{\partial}{\partial t}, \quad (4)$$

where C is any constant and $\hat{\mathbf{p}} = -i\frac{\partial}{\partial x}\hat{\mathbf{e}}_1 - i\frac{\partial}{\partial y}\hat{\mathbf{e}}_2$.

In this letter, we restrict ourselves to the case where the electromagnetic potentials are given by

$$\hat{\mathbf{A}} = \frac{B(t)}{2}(\hat{y}\hat{\mathbf{e}}_1 - \hat{x}\hat{\mathbf{e}}_2), \quad \hat{\phi}(t) = 0, \quad (5)$$

where $(\hat{\mathbf{e}}_1, \hat{\mathbf{e}}_2, \hat{\mathbf{e}}_3)$ are the unit vectors of the cartesian basis. With this choice, the magnetic and electric fields turn out to be

$$\mathbf{B} = B(t)\hat{\mathbf{e}}_3, \quad (6)$$

$$\mathbf{E} = \frac{1}{2}\rho\frac{dB(t)}{dt}\hat{\phi}, \quad (7)$$

where $(\hat{\rho}, \hat{\phi}, \hat{\mathbf{e}}_3)$ form the cylindrical basis. Hereafter, we will denote $\omega(t)$, $m(t)$ and $B(t)$ by ω , m and B , respectively, for brevity. By substituting Eq. (5) into Eq. (4), the Hamiltonian becomes

$$\frac{\hat{p}_x^2 + \hat{p}_y^2}{2m} - \frac{qB}{4m}(\hat{y}\hat{p}_x - \hat{x}\hat{p}_y) + \frac{m}{2}\left(\omega^2 + \frac{q^2 B^2}{4m^2}\right)(\hat{x}^2 + \hat{y}^2) + \frac{C}{m(\hat{x}^2 + \hat{y}^2)} = i\frac{\partial}{\partial t} \quad (8)$$

Now we want to make a transformation to get rid of the cross-term in Eq. (8). To do this, an orthogonal transformation is introduced [12].

$$\begin{pmatrix} \hat{x} \\ \hat{y} \end{pmatrix} = \begin{pmatrix} \cos\beta(t) & -\sin\beta(t) \\ \sin\beta(t) & \cos\beta(t) \end{pmatrix} \begin{pmatrix} \hat{x}' \\ \hat{y}' \end{pmatrix}, \quad (9)$$

The time-dependent transformation (9) implies the following transformations for the quadratic terms

$$\hat{p}_x^2 + \hat{p}_y^2 \rightarrow \hat{p}_{x'}^2 + \hat{p}_{y'}^2, \quad \hat{x}^2 + \hat{y}^2 \rightarrow \hat{x}'^2 + \hat{y}'^2, \quad (10)$$

and for the cross-term and time derivative

$$\hat{y}\hat{p}_x - \hat{x}\hat{p}_y \rightarrow \hat{y}'\hat{p}_{x'} - \hat{x}'\hat{p}_{y'} \quad (11)$$

$$\frac{\partial}{\partial t} \rightarrow \frac{\partial}{\partial t} + i\dot{\beta}(t)[\hat{y}'\hat{p}_{x'} - \hat{x}'\hat{p}_{y'}]. \quad (12)$$

To eliminate the cross-term from the Eq. (8), β is chosen as

$$\dot{\beta}(t) = \frac{qB}{4m}, \quad (13)$$

where dot denotes time derivation as usual. In this case, Eq. (8) becomes

$$\frac{\hat{p}_{x'}^2 + \hat{p}_{y'}^2}{2m} + \frac{m}{2} \left(\omega^2 + \frac{q^2 B^2}{4m^2} \right) (\hat{x}'^2 + \hat{y}'^2) + \frac{C}{m(\hat{x}'^2 + \hat{y}'^2)} = i \frac{\partial}{\partial t}. \quad (14)$$

Eq. (14) does not depend on the cross-term and the square of the angular frequency is shifted by an amount of $q^2 B^2 / (4m^2)$.

To remove the harmonic part, we make the transformation

$$\hat{p}_x' \rightarrow \hat{P}_1 = \hat{p}_x' + i\alpha(t)\hat{x}', \quad \hat{p}_y' \rightarrow \hat{P}_2 = \hat{p}_y' + i\alpha(t)\hat{y}', \quad (15)$$

$$\hat{x}' \rightarrow \hat{Q}_1 = \hat{x}', \quad \hat{y}' \rightarrow \hat{Q}_2 = \hat{y}', \quad (16)$$

where $\alpha(t)$ is a time-dependent function to be determined later. Since $\hat{\mathbf{p}} = -i\frac{\partial}{\partial x}\hat{\mathbf{e}}_1 - i\frac{\partial}{\partial y}\hat{\mathbf{e}}_2$, we observe that the transformation (15) is equivalent to the multiplication of the wave function by $\exp[-\alpha(t)(x'^2 + y'^2)/2]$.

Under the transformation (15), the time derivative operator becomes

$$\frac{\partial}{\partial t} \rightarrow \frac{\partial}{\partial t} - \dot{\alpha}(t) \left(\frac{\hat{Q}_1'^2 + \hat{Q}_2'^2}{2} \right), \quad (17)$$

Substituting Eqs. (15), (16) and (17) in (14), we get

$$\frac{\hat{P}_1^2 + \hat{P}_2^2}{2m} + \Omega^2(t) [\hat{Q}_1^2 + \hat{Q}_2^2] + \frac{C}{m(\hat{Q}_1^2 + \hat{Q}_2^2)} + i\frac{\alpha(t)}{m}(\hat{Q}_1\hat{P}_1 + \hat{Q}_2\hat{P}_2) = i\frac{\partial}{\partial t} + \frac{\alpha(t)}{m}, \quad (18)$$

where

$$\Omega^2(t) = \frac{m}{2} \left(\omega^2 + \frac{q^2 B^2}{4m^2} \right) - \frac{\alpha^2(t)}{2m} + i\frac{\dot{\alpha}(t)}{2}.$$

The time-dependent functions $\alpha(t)$ should be chosen so that harmonic term in the Hamiltonian vanishes.

$$\frac{m}{2} \left(\omega^2 + \frac{q^2 B^2}{4m^2} \right) - \frac{\alpha^2(t)}{2m} + i\frac{\dot{\alpha}(t)}{2} = 0. \quad (19)$$

Eq. (18) is simplified after the elimination of the harmonic part.

$$\frac{\hat{P}_1^2 + \hat{P}_2^2}{2m} + \frac{C}{m(\hat{Q}_1^2 + \hat{Q}_2^2)} + i\alpha(t) [\hat{Q}_1 \hat{P}_1 + \hat{Q}_2 \hat{P}_2] = i\frac{\partial}{\partial t} + \frac{\alpha(t)}{m}. \quad (20)$$

Now a velocity-dependent interaction term is contained in Eq. (20). To get rid of this term, we need another transformation.

$$\hat{P}_1 \rightarrow \hat{P}_1' = \mu(t)\hat{P}_1, \quad \hat{P}_2 \rightarrow \hat{P}_2' = \mu(t)\hat{P}_2 \quad (21)$$

$$\hat{Q}_1 \rightarrow \hat{Q}_1' = \frac{\hat{Q}_1}{\mu(t)}, \quad \hat{Q}_2 \rightarrow \hat{Q}_2' = \frac{\hat{Q}_2}{\mu(t)}, \quad (22)$$

then the time derivative operator becomes

$$\frac{\partial}{\partial t} \rightarrow \frac{\partial}{\partial t} - i\frac{\dot{\mu}(t)}{\mu(t)}(\hat{Q}_1' \hat{P}_1' + \hat{Q}_2' \hat{P}_2'). \quad (23)$$

If $\mu(t)$ is chosen so that

$$\alpha(t) = -\frac{\dot{\mu}(t)}{\mu(t)}, \quad (24)$$

then the velocity dependent interaction term vanishes. The new equation is just the equation of a particle under an inverse harmonic potential and with a time-dependent mass.

$$\hat{P}_1'^2 + \hat{P}_2'^2 + \frac{2C}{\hat{Q}_1'^2 + \hat{Q}_2'^2} = i2m\mu^2(t)\frac{\partial}{\partial t} + 2\mu^2(t)\alpha(t) = k^2. \quad (25)$$

Since left-hand side and right-hand side of (25) depend on different parameters, the two sides are equal to a constant, k^2 . We can rewrite Eq. (25) as a wave equation rather than an operator equation

$$-\frac{\partial^2 \Psi(x, y, t)}{\partial Q_1'^2} - \frac{\partial^2 \Psi(x, y, t)}{\partial Q_2'^2} + \frac{2C}{Q_1'^2 + Q_2'^2} \Psi(x, y, t) = i2m\mu^2 \frac{\partial \Psi(x, y, t)}{\partial t} + 2\mu^2 \alpha \Psi(x, y, t). \quad (26)$$

Using the separation of variables technique, we can solve Eq. (26).

Let us write $\Psi = R(Q_1', Q_2')T(t)$

$$T(t) = \exp \left[-i \int_0^t \frac{k^2 + 2\mu^2(t')\alpha(t')}{2m(t')\mu^2(t')} dt' \right]. \quad (27)$$

Coordinate-dependent part of Eq. (26) can be decomposed in polar coordinates

$$Q^2 \frac{d^2 Z}{dQ^2} + Q \frac{dZ}{dQ} + (k^2 Q^2 - 2C - n^2)Z = 0 \quad (28)$$

$$\frac{d^2 \Theta}{d\theta^2} = -n^2 \Theta, \quad (29)$$

where $Q^2 = Q_1'^2 + Q_2'^2$, $Q_1' = Q \cos \theta$, $Q_2' = Q \sin \theta$ and $R(Q_1', Q_2') = Z(Q)\Theta(\theta)$.

The relation between θ and x, y is given

$$\tan \theta = \frac{Q_2'}{Q_1'} = \frac{\cos \beta x + \sin \beta y}{-\sin \beta x + \cos \beta y} \quad (30)$$

where β was defined in Eq. (13).

If we introduce $\nu^2 = 2C + n^2$, we see that Eq. (28) is just the Bessel differential equation of order ν [13]. The solutions of (28,29)

$$Z(Q) = AJ_\nu(kQ) + BN_\nu(kQ) \quad (31)$$

$$\Theta = C \exp(\pm in\theta), \quad (32)$$

where $J_\nu(kQ')$, $N_\nu(kQ')$ are the Bessel function of the first and the second kind respectively. The constants A , B and C are determined from the boundary conditions. Note that ν and n are not the same. If the inverse harmonic potential term goes to zero, they become equal to each other.

Finally, the complete exact solution of Eq. (4) is given

$$\Psi = \left[AJ_\nu \left(k \frac{\sqrt{x^2 + y^2}}{\mu(t)} \right) + BN_\nu \left(k \frac{\sqrt{x^2 + y^2}}{\mu(t)} \right) \right] \exp[\alpha(t)(x^2 + y^2) \pm in\theta - if] \quad (33)$$

where $f(t) = \int_0^t \frac{k^2 + 2\mu^2(t')\alpha(t')}{2m(t')\mu^2(t')} dt'$ and α , μ , θ were defined Eqs. (19), (24) and (30) respectively.

In summary, the exact solution of the problem of the charged harmonic plus an inverse harmonic oscillator with time-dependent mass and frequency in a time-dependent electromagnetic field is obtained by making some appropriate transformation on momentum and coordinate operators.

REFERENCES

- [1] B. Sutherland, J. Math. Phys., **12** 246 (1971).
- [2] F. Calogero, J. Math. Phys. **12**, 419 (1971).
- [3] S. M Chumakov, V. V Dodonov, and V. I Man'ko, J. Phys. A. **19**, 3229 (1986).
- [4] V. V Dodonov, V. I Man'ko, and L. Rosa, Phys. Rev. A, **57**, 2851 (1998).
- [5] Maamache M, Phys. Rev. A, **61**, 026102 (2000).
- [6] Um CI, Shin SM, Yeon KH *et. al*, Phys. Rev. A, **58**, 1574 (1998).
- [7] Um CI, Shin SM, Yeon KH *et. al*, Phys. Rev. A, **61**, 026103 (2000).
- [8] Kaushal RS, Parashar D, Phys. Rev. A, **55** 2610 (1997).
- [9] J. M. Cervero, Int. J. Theor. Phys. **38**, 2095 (1999).
- [10] Pedrosa IA, Serra GP, Guedes I, Phys. Rev. A **56**, 4300 (1997).
- [11] M. M. Nieto and L. M. Simmons, Phys. Rev. D **20**, 1332 (1979).
- [12] A. de S. Dutra, C. F. de Souza and L. C. de Albuquerque, Phys. Lett. A **156**, 371 (1991).
- [13] G. B. Arfken and H. J. Weber, *Mathematical Methods for Physicists* (San Diego, Academic Press, 1995).